

TRANSMIT/RECEIVE SWITCH FOR AN RF TRANSCEIVER

BACKGROUND OF THE INVENTION

FIELD OF THE INVENTION

[0001] The invention relates to a transceiver for radio frequency signal, more particularly to respective switching of a receive branch or a transmit branch to an antenna. Such a transceiver can be used in a wireless local area network or in any other suitable wireless system.

DESCRIPTION OF THE RELATED ART

[0002] Transceivers for wireless systems such as wireless LANs, cellular or cordless telephone systems are well known in the art. In one type of transceivers, a transmit branch and a receive branch are respectively switched to an antenna, when the transceiver is in a transmit mode or in a receive mode, respectively. Reception or transmission may be in the same band or in separate bands. For respective switching of the transmit branch or the receive branch to the antenna, in known transceivers, a first switch is provided between an output stage of a power amplifier comprised in the transmit branch and an antenna feed point, a second switch is provided between the antenna feed point and an input stage of a low noise amplifier comprised in the receive branch.

SUMMARY OF THE INVENTION

[0003] It is an object of the invention to provide switching of a transmit branch in a transceiver to an antenna feed point that also under high voltage output signals delivered by a transmit power output stage causes no component break through or other problems.

[0004] To this end the transceiver comprises a transmit branch that is coupled to an antenna feed point, a receive branch comprising a first network with an output node and with an input node that is coupled to the antenna feed point, the first network being configured such that in a transmit mode of said transceiver said input node is switched as an open circuit by switching said output node as a short circuit.

effectively kept to a zero voltage level while still the low noise amplifier can draw current. Herewith, effectively, the input of the low noise amplifier acts as a short circuit when the transceiver is in the transmit mode.

[0009] In an embodiment, a tank circuit that is coupled to a transmit power output transistor is directly coupled to the antenna feed point. In this embodiment, when the transceiver is in receive mode, the transmit power output transistor is simply switched off so that its output is high-ohmic. This might cause some losses, when the transceiver is in receive mode, but such losses are typically low, as shown by simulations, no more than in the order of 1 dB. This solution allows very easy integration of the full transmit/receive antenna switch in an integrated circuit. This is because the transmitter, the receiver and the transmit/receive antenna switch can be integrated using the same RF silicon process, such as a QUBIC3 process.

[0010] In another embodiment, the tank circuit is coupled to the antenna feed point by a MOS switch between the tank circuit and the antenna feed point. Also in this embodiment, the transmit power output transistor is switched off when the transceiver is in receive mode. Although in this embodiment the transmit antenna switch part is not so easy to integrate in an integrated circuit, reduced loss is obtained when the transceiver is in receive mode. This is because a different RF silicon process is needed to implement the transmit antenna switch part, to prevent break through, such as an RF GaAs process.

BRIEF DESCRIPTION OF THE DRAWING

[0011] Figure 1 is a diagram of a transceiver according to the invention.

[0012] Figure 2 is circuit diagram of an input stage of a low noise amplifier including a switch according to the invention.

[0013] Figure 3 is an embodiment of network of the invention.

[0014] Figure 4 shows a transmit antenna switch part in a transmit/receive switch according to the invention.

[0015] Throughout the figures the same reference numerals are used for indicating the same elements.

DESCRIPTION OF THE DETAILED EMBODIMENTS

0986235-053504
FIG. 1

[00016] Figure 1 is a diagram of a transceiver 1 according to the invention. Such a transceiver 1 may be part of an apparatus such as a wireless network apparatus, a cell phone, a cordless phone, a PDA, a PC with a wireless module, or the like. The transceiver 1 may also be included in a radio frequency transceiver module to be used in an apparatus or system, or a combination of devices. The transceiver 1 comprises a transmit branch Tx and a receive branch Rx. In transmit branch Tx, a transmit power transistor 2 is shown that is coupled to a transmit tank circuit 3 comprised of an inductor 4, a capacitor 5 and a capacitor 6. The tank circuit 3 is coupled to an antenna feed point 7 to which an antenna 8 is or can be connected. In receive branch Rx, a low noise amplifier (LNA) 9 is shown that is coupled to the antenna feed point 7 via a network 10. In the shown embodiment, network 10 comprises a capacitor 11 that is coupled between an input node of network 10 and ground, an inductor 12 between antenna feed point 7 and an output node of network 10, and an NMOS switch 13 between the output node and ground. Transceiver 1 further comprises control means 14 to control the transceiver 1 to adopt a transmit mode or a receive mode, respectively. In transmit mode, NMOS switch 13 switches the output node to ground, i.e., the output node is short-circuited, thereby, through network 10 that performs impedance transformation, causing the input node to become an open circuit. LC-network 10 has two purposes, first to isolate receive branch Rx from the antenna 8 by creating a short circuit at the output which is seen as an open circuit at the input, and second to transfer the antenna signal to an input of low noise amplifier 9 by opening the short at the output. The ratio of the LC can be used to match the antenna impedance, typically 50 Ohms, to the input impedance of LNA 9.

[00017] Figure 2 is circuit diagram of an input stage 20 of a low noise amplifier including a switch 21 according to the invention. Input stage 20 comprises cascoded transistors 22 and 23 of which transistor 23 is an input transistor that is coupled to inductor 12 shown in Figure 1, and of which transistor 22 is an output transistor. In this embodiment, through a feedback mechanism whereby transistor 21 closes a feedback path when transceiver 1 is in transmit mode, the input voltage of low noise amplifier input stage 20 is kept low, zero or close to zero, so that the input impedance of input stage 20 is low or zero. Herewith, effectively a short circuit situation is obtained. Further

shown in Figure 2 are a DC-blocking capacitor 24, a load resistor 25, a current source 26, and a capacitor 27.

[00018] Figure 3 is an embodiment of network 10 of the invention. In this embodiment, network 10 comprises a $1/4$ - λ transmission line 30, embodied as a micro-strip line, and a switch 31 to ground. Switch 31 may be an RF Reed relays. Transmission line 30 is a bi-directional element that transforms a short circuit to an open circuit and vice versa. Network 10 has two purposes, first to isolate receive branch Rx from the antenna 8 by creating a short circuit at the output which is seen as an open circuit at the input, and second to transfer the antenna signal to an input of low noise amplifier 9 by opening the short at the output. The impedance of the micro-strip line can be used to match the antenna impedance, typically 50 Ohms, to the input impedance of LNA 9.

[00019] Figure 4 shows a transmit antenna switch part in a transmit/receive switch according to the invention comprising an NMOS transmit switch 40. With transceiver 1 in receive mode with transistor 2 switched off, switch 40 is open thereby blocking reception energy to enter transmit branch Tx.

[00020] In view of the foregoing it will be evident to a person skilled in the art that various modifications may be made within the spirit and the scope of the invention as hereinafter defined by the appended claims and that the invention is thus not limited to the examples provided. The word "comprising" does not exclude the presence of other elements or steps than those listed in a claim.